

BUZZARDEYE



- ❖ 1 PCs 4-Ch H.264 AHD DVR
- ❖ 4 PCs 2MP AHD Cameras
- ❖ 4 Set 18.3 meter cable with connectors
- ❖ 1 PC 12V5A Adaptor
- ❖ IP66, outdoor installation

Model	BEV-KIT-IN1AHD-40
Image Sensor	1/3" CMOS 2.0 MEGAPIXEL
Effective Pixels	1920(H) x 1080(V)
IR Led	2xHLEDs
IR Distance	30-40m, Smart IR
Lens	3.6mm
Operation System	Embedded LINUX
Video Input	4Ch BNC
Image encoding	H.264
Display Image	1080P*4Ch
Playback	PAL: 1080P*4CH@25FPS; NTSC: 1080P*4CH@30FPS
Motion Detection	Each channel can be set for detection; Sensitivity Level 1-6
Recording Mode	Manual, Motion Detection, Alarm, Time Recording
Data Save	HDD, Network
Backup Mode	HDD, USB pen drive store and backup
HDD	1 SATA Slot up to 4TB
Audio	4 Ch In; 1 Ch Out